



BF0910D



BF2600D



BF9400E

new



BF15000E + BFX44



BF00...

type	rated current		kW rating		control	description	auxiliary contacts
	(AC1)	(AC3)	(AC3) 400V				
Three-pole contactors (Ui 690V) - DC control circuit							
Permanent magnet types (Ui 690V) - DC control circuit (low consumption coil 5.4 watt)							
BF0910D...	25A	9A	4.2kW		DC	3-pole contactor	1NO
BF1210D...	28A	12A	5.7kW		DC	3-pole contactor	1NO
BF1810D...	32A	18A	7.5kW		DC	3-pole contactor	1NO
BF2510D...	32A	25A	12.5kW		DC	3-pole contactor	1NO
BF2600D...	45A	26A	13.0kW		DC	3-pole contactor	-
BF3200D...	56A	32A	16.0kW		DC	3-pole contactor	-
BF3800D...	56A	38A	18.5kW		DC	3-pole contactor	-
<i>Standard coil voltages (add to part number): DC - 012/024/048/060/110/220V</i>							
Extra-low consumption coil 2.4 watt (ideal for direct PLC interfacing)							
BF0910L...*	25A	9A	4.2kW		DC	3-pole contactor	1NO
BF1210L...*	28A	12A	5.7kW		DC	3-pole contactor	1NO
BF1810L...*	32A	18A	7.5kW		DC	3-pole contactor	1NO
BF2510L...*	32A	25A	12.5kW		DC	3-pole contactor	1NO
BF3200L...*	56A	32A	16.0kW		DC	3-pole contactor	-
BF3800L...*	56A	38A	18.5kW		DC	3-pole contactor	-
<i>* Extra low consumption DC coil voltages (add to part number): 024/048 VDC</i>							
AC/DC electronically controlled coil (wide voltage range)							
BF4000E...	70A	40A	18.5kW		AC/DC	3-pole contactor	-
BF5000E...	90A	50A	22kW		AC/DC	3-pole contactor	-
BF6500E...	100A	65A	30kW		AC/DC	3-pole contactor	-
BF8000E...	115A	80A	45kW		AC/DC	3-pole contactor	-
BF9400E...	115A	95A	55kW		AC/DC	3-pole contactor	-
BF9500E...	140A	95A	55kW		AC/DC	3-pole contactor	-
BF11500E...	160A	115A	55kW		AC/DC	3-pole contactor	-
BF15000E...	165A	150A	75kW		AC/DC	3-pole contactor	-
<i>"E" standard voltage coils (add to part number) - 024=20...48V / 110=60...110V / 230=100...250V AC/DC</i>							
<i>Larger sizes 250...630A - see page A-2 AC/DC contactors</i>							
Four-pole contactors (Ui 690V) - DC control circuit							
type	rated current		kW (AC1)		control	description	auxiliary contacts
	(lth)	(AC1)	230V	400V			
Permanent magnet types (Ui 690V) - DC control circuit							
BF09T4D...	25A	25A	9.5	16	DC	4-pole contactor	4NO
BF18T4D...	32A	32A	12	21	DC	4-pole contactor	4NO
Attachable 4th pole - for above 3-pole contactors BF26 - 150							
<i>Add following attachable 4th pole to above 3 pole contactors to make up a 4 pole contactor</i>							
BFXD42	56A		attachable 4th pole for 3-pole contactors				BF26/32/38D/L
BFX43	115A		attachable 4th pole for 3-pole contactors				BF40...80A/E
BFX44	165A		attachable 4th pole for 3-pole contactors				BF95...150A/E
<i>Larger sizes B250...630 - see page A-2 AC/DC contactors</i>							
Special pole configuration contactors							main cont.
BF18T2D...	32A	32A	10	18	DC	4-pole contactor	2NO + 2NC
BF26T2D...	45A	45A	12	21	DC	4-pole contactor	2NO + 2NC
BF38T2D...	56A	56A	17	30	DC	4-pole contactor	2NO + 2NC
BF80T2E...	115A	115A	43	76	AC/DC	4-pole contactor	2NO + 2NC
BF18T0D...	32A	32A	10	18	DC	4-pole contactor	4NC
BF26T0D...	45A	45A	12	21	DC	4-pole contactor	4NC
Control relays - DC control circuit (extra-low consumption coil 2.4 watt)							
BF0040L...	10A	10A	-	-	DC	control relay	4NO
BF0031L...	10A	10A	-	-	DC	control relay	3NO + 1NC
BF0022L...	10A	10A	-	-	DC	control relay	2NO + 2NC
BF0004L...	10A	10A	-	-	DC	control relay	4NC