



type	AC-21A ≤ 690V	AC-23A ≤ 415V	poles	description	dimensions (mm) (H) (W) (D)		
<b>GA series - 3 pole load-break switches</b>				<b>16A - 160A</b>			
<ul style="list-style-type: none"> <li>Modular design DIN rail mountable supplied with direct mounted padlockable handle</li> <li>Door interlocking handle and shaft (<i>to be ordered separately</i>)</li> <li>Attachable 4th pole for all switches</li> </ul>							
<b>GA016A</b>	16A	7.5kW	3 pole	Isolator/load-break switch	78	36	75
<b>GA025A</b>	25A	11.0kW	3 pole	Isolator/load-break switch	78	36	75
<b>GA032A</b>	32A	15.0kW	3 pole	Isolator/load-break switch	78	36	75
<b>GA040A</b>	40A	18.5kW	3 pole	Isolator/load-break switch	78	36	75
<b>GA063SA</b>	63A	22.0kW	3 pole	Isolator/load-break switch	78	36	75
<b>GA063A</b>	63A	30kW	3 pole	Isolator/load-break switch	100	70	75
<b>GA080A</b>	80A	45kW	3 pole	Isolator/load-break switch	100	70	75
<b>GA125A</b>	125A	55kW	3 pole	Isolator/load-break switch	100	70	75
<b>GA160A</b>	160A	55kW	3 pole	Isolator/load-break switch	100	70	75
<b>GL series - 3 pole load-break switches</b>				<b>160A - 315A</b>			
<ul style="list-style-type: none"> <li>Modular design DIN rail or chassis mountable</li> <li>Door interlocking handle and shaft or direct mount handle (<i>to be ordered separately</i>)</li> <li>Visual contacts (<i>window on individual power poles clearly indicates switch status</i>)</li> <li>Easy shaft mount and removal (<i>snap-on with front mounted release lever</i>)</li> <li>Clip-on auxiliary contact (<i>up to 8 per switch</i>)</li> <li>Attachable 4th pole for all switches</li> </ul>							
<b>GL0160C1</b>	160A	90kW	3 pole	Isolator/load-break switch	155	162	91
<b>GL0200C1</b>	200A	110kW	3 pole	Isolator/load-break switch	155	162	91
<b>GL0250C1</b>	250A	140kW	3 pole	Isolator/load-break switch	155	162	91
<b>GL0315C1</b>	315A	140kW	3 pole	Isolator/load-break switch	155	162	91
<b>Attachable 4th pole</b>				<b>(for above 3 pole switches)</b>			
<b>GAX42040A</b>	40A	18.5kW	1 pole	attachable 4th pole for switches	GA016...40A		
<b>GAX42063SA</b>	63A	22kW	1 pole	attachable 4th pole for switches	GA063SA		
<b>GAX42063A</b>	63A	22kW	1 pole	attachable 4th pole for switches	GA063A		
<b>GAX42125A</b>	125A	55kW	1 pole	attachable 4th pole for switches	GA063...125A		
<b>GAX42160A</b>	160A	55kW	1 pole	attachable 4th pole for switches	GA160A		
<b>GAX41040A</b>	40A	18.5kW	1 pole	4th pole for switches ( <i>early-make</i> )	GA016...40A		
<b>GAX41125A</b>	125A	55kW	1 pole	4th pole for switches ( <i>early-make</i> )	GA063...125A		
<b>GLX420315</b>	315A	132kW	1 pole	attachable 4th pole for switches	GL0160...315A		
<b>Handles (external front operation)</b>				<b>(IP65)</b>			
<ul style="list-style-type: none"> <li>External door interlocking handles padlockable (3 padlocks) in "OFF" position</li> </ul>							
<b>GAX61</b>	red/yellow	door interlocking handle 65 mm <sup>2</sup> ( <i>screw fixing</i> )		GA016...160A			
<b>GAX63</b>	red/yellow	door interlocking handle 65 mm <sup>2</sup> ( <i>ring fix Ø 22 mm</i> )		GA016...160A			
<b>GAX64</b>	red/yellow	as above - defeatable 65 mm <sup>2</sup> ( <i>ring fix Ø 22 mm</i> )		GA016...160A			
<b>GAX68</b>	red/yellow	door interlocking handle 48 mm <sup>2</sup> ( <i>screw fixing</i> )		GA016...63SA			
<b>GAX66N*</b>	red/yellow	door interlocking pistol grip handle - ( <i>defeatable</i> )		GA063...160A			
<b>GAX66NB*</b>	black	door interlocking pistol grip handle - ( <i>defeatable</i> )		GA063...160A			
* Requires <b>GAX60B</b> adaptor (below) and 7 mm <sup>2</sup> extension shaft							
<b>GAX60B</b>	adaptor to accommodate 7 mm <sup>2</sup> shaft required	for handles		GAX66N/NB			
<b>GLX61</b>	red/yellow	door interlocking pistol grip handle (125 mm)		GL0160...315A			
<b>GLX61B</b>	black	door interlocking pistol grip handle (125 mm)		GL0160...315A			
<b>GLX00</b>	-	shaft alignment ring for above handles		GL0160...315A			
<b>Direct switch mounted handle</b>							
<b>GLX61DB</b>	black	snap-on direct switch mount internal handle		GL0160...315A			
<b>GLX61D</b>	red/yellow	snap-on direct switch mount internal handle		GL0160...315A			
<b>Extension shafts (for above handles)</b>							
<b>GAX7200</b>	200 mm	5 mm <sup>2</sup>	extension shaft for switches	GA016...63SA			
<b>GAX7300</b>	300 mm	5 mm <sup>2</sup>	extension shaft for switches	GA016...63SA			
<b>GAX7200AN</b>	200 mm	7 mm <sup>2</sup>	extension shaft for handle <b>GAX66N..</b>	GA063...160A			
<b>GAX7300AN</b>	300 mm	7 mm <sup>2</sup>	extension shaft for handle <b>GAX66N..</b>	GA063...160A			
<b>GLX7200S10</b>	200 mm	10 mm <sup>2</sup>	extension shaft for switches	GL0160...315A			
<b>GLX7300S10</b>	300 mm	10 mm <sup>2</sup>	extension shaft for switches	GL0160...315A			
<b>GLX7400S10</b>	400 mm	10 mm <sup>2</sup>	extension shaft for switches	GL0160...315A			
<b>GLX7500S10</b>	500 mm	10 mm <sup>2</sup>	extension shaft for switches	GL0160...315A			