



BF0910D



BF2600D



new

BF8000E



B11500



BF00...

type	rated current (lth)	(AC3)	kW rating (AC3) 400V	control	description	auxiliary contacts
Three-pole contactors (Ui 690V)						
Permanent magnet types (Ui 690V) - DC control (low consumption coil 5.4 watt)						
BF0910D	25A	9A	4.2kW	DC	3-pole contactor	1NO
BF1210D	28A	12A	5.7kW	DC	3-pole contactor	1NO
BF1810D	32A	18A	7.5kW	DC	3-pole contactor	1NO
BF2510D	32A	25A	12.5kW	DC	3-pole contactor	1NO
BF2600D	45A	26A	13.0kW	DC	3-pole contactor	-
BF3200D	56A	32A	16.0kW	DC	3-pole contactor	-
BF3800D	56A	38A	18.5kW	DC	3-pole contactor	-
Permanent magnet types (Ui 690V) - DC control (extra-low consumption coil 2.4 watt)						
BF0910L...□	25A	9A	4.2kW	DC	3-pole contactor	1NO
BF1210L...□	28A	12A	5.7kW	DC	3-pole contactor	1NO
BF1810L...□	32A	18A	7.5kW	DC	3-pole contactor	1NO
BF2510L...□	32A	25A	12.5kW	DC	3-pole contactor	1NO
BF3200L...□	56A	32A	16.0kW	DC	3-pole contactor	-
BF3800L...□	56A	38A	18.5kW	DC	3-pole contactor	-
□ Standard DC extra-low consumption coil voltages 024/048 VDC						
AC/DC control (Ui 1000V) (BF40 - 80E wide voltage range coil) 20 - 48V/60 - 110V/100 - 250V						
BF4000E	70A	40A	18.5kW	AC/DC	3-pole contactor	-
BF5000E	90A	50A	22kW	AC/DC	3-pole contactor	-
BF6500E	110A	65A	30kW	AC/DC	3-pole contactor	-
BF8000E	115A	80A	45kW	AC/DC	3-pole contactor	-
BF95C00	125A	95A	50kW	DC	3-pole contactor	-
B11500	160A	110A	61kW	AC/DC	3-pole contactor	-
B14500	250A	150A	80kW	AC/DC	3-pole contactor	-
B18000	275A	185A	100kW	AC/DC	3-pole contactor	-
B25000	350A	265A	140kW	AC/DC	3-pole contactor	-
B31000	450A	320A	170kW	AC/DC	3-pole contactor	-
B40000	550A	420A	225kW	AC/DC	3-pole contactor	-
B50000	700A	520A	290kW	AC/DC	3-pole contactor	-
B63000	800A	630A	335kW	AC/DC	3-pole contactor	-
Four-pole contactors (Ui 690V)						
type	rated current (lth)		kW (AC1) 230V 400V	control	description	auxiliary contacts
Permanent magnet types (Ui 690V) - DC control						
BF09T4D	25A		9.5 16	DC	4-pole contactor	4NO
BF18T4D	32A		12 21	DC	4-pole contactor	4NO
AC/DC control - (Ui 1000V)						
B115400	160A		57 98	AC/DC	4-pole contactor	4NO
B145400	250A		91 150	AC/DC	4-pole contactor	4NO
B180400	275A		95 160	AC/DC	4-pole contactor	4NO
B250400	350A		124 214	AC/DC	4-pole contactor	4NO
B310400	450A		158 270	AC/DC	4-pole contactor	4NO
B400400	550A		200 345	AC/DC	4-pole contactor	4NO
B500400	700A		252 438	AC/DC	4-pole contactor	4NO
B630400	800A		288 500	AC/DC	4-pole contactor	4NO
BF18T2D	32A		10 18	DC	4-pole contactor	2NO+2NC
BF26T2D	45A		12 21	DC	4-pole contactor	2NO+2NC
BF38T2D	56A		17 30	DC	4-pole contactor	2NO+2NC
BF80T2E	115A		43 76	AC/DC	4-pole contactor	2NO+2NC
BF18T0D	32A		10 18	DC	4-pole contactor	4NC
BF26T0D	45A		12 21	DC	4-pole contactor	4NC
Note: Standard coil voltages 012/024/048/110/220 VDC – add to part number (other voltages on request)						
Control relays DC 24 VDC/48 VDC						
BF0040L	10A		- -	DC	control relay	4NO
BF0031L	10A		- -	DC	control relay	3NO+1NC
BF0022L	10A		- -	DC	control relay	2NO+2NC
BF0004L	10A		- -	DC	control relay	4NC