



BF0910A



BF2600A



BF5000A



B11500



B25000



B115400



BF00...

type	rated current (lth)	rated current (AC3)	kW rating (AC3) 400V		control	description	auxiliary contacts
Three-pole contactors (Ui 690V)							
BF0910A	25A	9A	4.2kW		AC	3-pole contactor	1NO
BF0901A	25A	9A	4.2kW		AC	3-pole contactor	1NC
BF1210A	28A	12A	5.7kW		AC	3-pole contactor	1NO
BF1201A	28A	12A	5.7kW		AC	3-pole contactor	1NC
BF1810A	32A	18A	7.5kW		AC	3-pole contactor	1NO
BF1801A	32A	18A	7.5kW		AC	3-pole contactor	1NC
BF2510A	32A	25A	12.5kW		AC	3-pole contactor	1NO
BF2501A	32A	25A	12.5kW		AC	3-pole contactor	1NC
BF2600A	45A	26A	13.0kW		AC	3-pole contactor	-
BF3200A	56A	32A	16.0kW		AC	3-pole contactor	-
BF3800A	56A	38A	18.5kW		AC	3-pole contactor	-
Three-pole contactors (Ui 1000V)							
BF4000A	70A	40A	18.5kW		AC	3-pole contactor	-
BF5000A	90A	50A	22kW		AC	3-pole contactor	-
BF6500A	100A	65A	30kW		AC	3-pole contactor	-
BF8000A	115A	80A	45kW		AC	3-pole contactor	-
BF9500	125A	95A	50kW		AC	3-pole contactor	-
BF11000	125A	110A	61kW		AC	3-pole contactor	-
B11500	160A	110A	61kW		AC/DC	3-pole contactor	-
B14500	250A	150A	80kW		AC/DC	3-pole contactor	-
B18000	275A	185A	100kW		AC/DC	3-pole contactor	-
B25000	350A	265A	140kW		AC/DC	3-pole contactor	-
B31000	450A	320A	170kW		AC/DC	3-pole contactor	-
B40000	550A	420A	225kW		AC/DC	3-pole contactor	-
B50000	700A	520A	290kW		AC/DC	3-pole contactor	-
B63000	800A	630A	335kW		AC/DC	3-pole contactor	-
B125024	1250A	-	(AC1) 830kW		AC	3-pole contactor	-
B160024	1600A	-	950kW		AC	3-pole contactor	-
Four-pole contactors (Ui 1000V)							
type	rated current (lth)	rated current (AC1)	kW (AC1) 230V 400V		control	description	main contacts
4th pole attachment for contactors BF26 - 80A							
<i>attach 4th pole (below) to above 3 pole contactors to make up a 4 pole contactor</i>							
BFX42	56A	-	attachable 4th pole for contactors		-	-	BF26 - 38A
BFX43	115A	-	attachable 4th pole for contactors		-	-	BF40 - 80A
B115400	160A	-	57	98	AC/DC	4-pole contactor	4NO
B145400	250A	-	91	150	AC/DC	4-pole contactor	4NO
B180400	275A	-	95	160	AC/DC	4-pole contactor	4NO
B250400	350A	-	124	214	AC/DC	4-pole contactor	4NO
B310400	450A	-	158	270	AC/DC	4-pole contactor	4NO
B400400	550A	-	200	345	AC/DC	4-pole contactor	4NO
B500400	700A	-	252	438	AC/DC	4-pole contactor	4NO
B630400	800A	-	288	500	AC/DC	4-pole contactor	4NO
Four-pole contactors (Ui 690V)							
BF09T4A	25A	-	9.5	16	AC	4-pole contactor	4NO
BF12T4A	28A	-	10	18	AC	4-pole contactor	4NO
BF18T4A	32A	-	12	21	AC	4-pole contactor	4NO
BF09T2A	25A	-	9.5	16	AC	4-pole contactor	2NO+2NC
BF18T2A	32A	-	10	18	AC	4-pole contactor	2NO+2NC
BF26T2A	45A	-	12	21	AC	4-pole contactor	2NO+2NC
BF38T2A	56A	-	17	30	AC	4-pole contactor	2NO+2NC
BF80T2A	115A	-	43	76	AC	4-pole contactor	2NO+2NC
BF18T0A	32A	-	21	36	AC	4-pole contactor	4NC
Control relays							
BF0040A	10A	-	-	-	AC	control relay	4NO
BF0031A	10A	-	-	-	AC	control relay	3NO+1NC
BF0022A	10A	-	-	-	AC	control relay	2NO+2NC
BF0004A	10A	-	-	-	AC	control relay	4NC

Note: Standard coil voltages 012/024/048/110/220 V – add to part number (other voltages on request)