



BF0910A



BF2600A



BF5000A



BF15000A

new



B25000



BF00...

type	rated current		kW rating		control	description	auxiliary contacts
	(AC1)	(AC3)	(AC3)	400V			
Three-pole contactors (Ui 690V) / AC control circuit							
BF0910A...	25A	9A	4.2kW		AC	3-pole contactor	1NO
BF0901A...	25A	9A	4.2kW		AC	3-pole contactor	1NC
BF1210A...	28A	12A	5.7kW		AC	3-pole contactor	1NO
BF1201A...	28A	12A	5.7kW		AC	3-pole contactor	1NC
BF1810A...	32A	18A	7.5kW		AC	3-pole contactor	1NO
BF1801A...	32A	18A	7.5kW		AC	3-pole contactor	1NC
BF2510A...	32A	25A	12.5kW		AC	3-pole contactor	1NO
BF2501A...	32A	25A	12.5kW		AC	3-pole contactor	1NC
BF2600A...	45A	26A	13.0kW		AC	3-pole contactor	-
BF3200A...	56A	32A	16.0kW		AC	3-pole contactor	-
BF3800A...	56A	38A	18.5kW		AC	3-pole contactor	-
Three-pole contactors (Ui 1000V) / AC control circuit							
BF4000A...	70A	40A	18.5kW		AC	3-pole contactor	-
BF5000A...	90A	50A	22kW		AC	3-pole contactor	-
BF6500A...	100A	65A	30kW		AC	3-pole contactor	-
BF8000A...	115A	80A	45kW		AC	3-pole contactor	-
BF9400A...	115A	95A	55kW		AC	3-pole contactor	-
BF9500A...	140A	95A	55kW		AC	3-pole contactor	-
BF11500A...	160A	115A	55kW		AC	3-pole contactor	-
BF15000A...	165A	150A	75kW		AC	3-pole contactor	-
B14500...	250A	150A	80kW		AC/DC	3-pole contactor	-
B18000...	275A	185A	100kW		AC/DC	3-pole contactor	-
B25000...	350A	265A	140kW		AC/DC	3-pole contactor	-
B31000...	450A	320A	170kW		AC/DC	3-pole contactor	-
B40000...	550A	420A	225kW		AC/DC	3-pole contactor	-
B50000...	700A	520A	290kW		AC/DC	3-pole contactor	-
B63000...	800A	630A	335kW		AC/DC	3-pole contactor	-
B125024...	1250A	-	(AC1) 830kW		AC/DC	3-pole contactor	2NO + 4NC
B160024...	1600A	-	(AC1) 950kW		AC/DC	3-pole contactor	2NO + 4NC
<i>Standard coil voltages (add to part number): AC - 024/048/110/230/400V others available on request</i>							
Four-pole contactors / AC control circuit							
type	rated current		kW (AC1)		control	description	main contacts
	lth (AC1)	(AC1)	230V	400V			
BF09T4A...	25A	-	9.5	16	AC	4-pole contactor	4NO
BF12T4A...	28A	-	10	18	AC	4-pole contactor	4NO
BF18T4A...	32A	-	12	21	AC	4-pole contactor	4NO
BF26T4A...	45A	-	17	30	AC	4-pole contactor	4NO
BF38T4A...	56A	-	21	36	AC	4-pole contactor	4NO
Attachable 4th pole - for above 3 pole contactors BF26 - 150							
<i>Add following attachable 4th pole to above 3 pole contactors to make up a 4 pole contactor</i>							
BFX42	56A		attachable 4th pole for 3-pole contactors			BF26/32/38A	
BFX43	115A		attachable 4th pole for 3-pole contactors			BF40...80A/E	
BFX44	165A		attachable 4th pole for 3-pole contactors			BF95...150A/E	
B145400...	250A	-	91	150	AC/DC	4-pole contactor	4NO
B180400...	275A	-	95	160	AC/DC	4-pole contactor	4NO
B250400...	350A	-	124	214	AC/DC	4-pole contactor	4NO
B310400...	450A	-	158	270	AC/DC	4-pole contactor	4NO
B400400...	550A	-	200	345	AC/DC	4-pole contactor	4NO
B500400...	700A	-	252	438	AC/DC	4-pole contactor	4NO
B630400...	800A	-	288	500	AC/DC	4-pole contactor	4NO
Special pole configurations contactors							
BF09T2A...	25A	-	9.5	16	AC	4-pole contactor	2NO + 2NC
BF18T2A...	32A	-	10	18	AC	4-pole contactor	2NO + 2NC
BF26T2A...	45A	-	12	21	AC	4-pole contactor	2NO + 2NC
BF38T2A...	56A	-	17	30	AC	4-pole contactor	2NO + 2NC
BF80T2A...	115A	-	43	76	AC/DC	4-pole contactor	2NO + 2NC
BF18T0A...	32A	-	21	36	AC	4-pole contactor	4NC
Control relays / AC control circuit							
BF0040A...	10A	-	-	-	AC	control relay	4NO
BF0031A...	10A	-	-	-	AC	control relay	3NO + 1NC
BF0022A...	10A	-	-	-	AC	control relay	2NO + 2NC
BF0004A...	10A	-	-	-	AC	control relay	4NC
<i>Standard coil voltages (add to part number): AC - 024/048/110/230/400V others available on request</i>							