



GAZ025



GAZ040



GAX42040A



GAX391

GA series enclosed switch disconnectors are supplied in robust, heavy duty enclosures made of ABS material in an IP65 execution with a sealable front cover.

The enclosures incorporate a red/yellow operating handle mechanically interlocked with cover in "ON" position, padlockable (3 padlocks) in the "OFF" position.

type	AC-21A	AC-23A	description	dimensions (mm)		
	≤ 690V	≤ 415V		(H)	(W)	(D)

Enclosed isolators 3 and 4 pole (IP65)

GAZ016	16A	7.5kW	3-pole enclosed load-break switch	160	100	120
GAZ025	25A	11.0kW	3-pole enclosed load-break switch	160	100	120
GAZ032	32A	15.0kW	3-pole enclosed load-break switch	160	100	120
GAZ040	40A	18.5kW	3-pole enclosed load-break switch	160	100	120
GAZ063EM	63A	22.0kW	3-pole enclosed load-break switch	160	100	120
GAZ063C	63A	30.0kW	3-pole enclosed load-break switch	210	175	122
GAZ080C	80A	45.0kW	3-pole enclosed load-break switch	210	175	122
GAZ125EM	125A	55.0kW	3-pole enclosed load-break switch	210	175	122
GAZ160EM	160A	55.0kW	3-pole enclosed load-break switch	210	175	122

For 4 pole - add attachable 4th pole (below) to above switches

Empty enclosures only (with red/yellow handle and extension shaft)

GAZ1	63A	empty enclosure with handle and extension shaft	160	100	97
GAZ2	160A	empty enclosure with handle and extension shaft	210	175	99

Enclosed changeover switches (I-O-II) 3 and 4 pole (IP65)

GAZ025 ET6	25A	11.0kW	3-pole enclosed changeover switch	210	175	122
GAZ040 ET6	40A	18.5kW	3-pole enclosed changeover switch	210	175	122
GAZ063 ET6	63A	30.0kW	3-pole enclosed changeover switch	280	220	208
GAZ080 ET6	80A	45.0kW	3-pole enclosed changeover switch	280	220	208
GAZ125 ET6	125A	55.0kW	3-pole enclosed changeover switch	280	220	208

For 4 pole - add attachable 4th pole (below) to above switches

Attachable 4th pole for above switches

GAX42040A	40A	attachable 4th pole for above switches	GA016-40A
GAX42063A	63A	attachable 4th pole for above switches	GA063A
GAX42125A	125A	attachable 4th pole for above switches	GA080-125A
GAX42160A	160A	attachable 4th pole for above switches	GA080-160A
GAX41040A	40A	attachable early-make 4th pole for above	GA016-40A
GAX41125A	125A	attachable early-make 4th pole for above	GA063-125A

Terminal shrouds

GAX81	1 pole	terminal protection shroud (set of 2 pcs)	GA016-40A/C
GAX82	1 pole	terminal protection shroud (set of 2 pcs)	GA063-160A/C
GAX83	3 pole	terminal protection shroud (set of 2 pcs)	GA016-40A/C
GAX84	3 pole	terminal protection shroud (set of 2 pcs)	GA063-160A/C

3 pole fuse holder for load-break switches 16 - 32A (for cylindrical 10x38mm fuses)

GAX391	1 0x 38	3ph fuse holder (attaches onto switches)	GA016A - 032A
---------------	---------	--	---------------