









	type	AC-21A ≤ 690V	AC-23A ≤ 415V	description	dimensions (mm) (H) (W) (D)					
 <p>GA016A</p>  <p>GA125A</p>  <p>GA080C</p>  <p>GAX1011A</p>  <p>GAX61</p>  <p>GAX63</p>  <p>GAX7200</p>  <p>GAX60B</p>	GA series 3-pole load-break switches (4th pole attachable)									
	<ul style="list-style-type: none"> Modular design DIN rail mountable supplied with direct mounted handle Door interlocking handle and shaft (to be ordered separately) 									
	GA016A	16A	7.5kW	3-pole load-break switch	78	36	75			
	GA025A	25A	11.0kW	3-pole load-break switch	78	36	75			
	GA032A	32A	15.0kW	3-pole load-break switch	78	36	75			
	GA040A	40A	18.5kW	3-pole load-break switch	78	36	75			
	GA063SA	63A	22.0kW	3-pole load-break switch	78	36	75			
	GA063A	63A	30.0kW	3-pole load-break switch	100	70	75			
	GA080A	80A	45.0kW	3-pole load-break switch	100	70	75			
	GA125A	125A	55.0kW	3-pole load-break switch	100	70	75			
GA160A	160A	55.0kW	3-pole load-break switch	100	70	75				
GAX42040A	40A		attachable 4th pole for above switches	GA016-40A						
GAX42063SA	63A		attachable 4th pole for above switches	GA063SA						
GAX42125A	125A		attachable 4th pole for above switches	GA063-125A						
GAX42160A	160A		attachable 4th pole for above switches	GA160A						
GAX41040A	40A		attachable early-make 4th pole for above switches	GA016-40A						
GAX41063SA	63A		attachable early-make 4th pole for above switches	GA016-63SA						
GAX41125A	125A		attachable early-make 4th pole for above switches	GA063-125A						
Direct door mounting version (rear access terminals) with shaft										
GA025C	25A	11.0kW	3-pole load-break switch	78	36	73				
GA040C	40A	18.5kW	3-pole load-break switch	78	36	73				
GA080C	80A	45.0kW	3-pole load-break switch	100	70	70				
GA125C	125A	55.0kW	3-pole load-break switch	100	70	70				
GAX42040C	40A		attachable 4th pole for above switches	GA016-40C						
GAX42125C	125A		attachable 4th pole for above switches	GA080-125C						
GAX41040C	40A		attachable early-make 4th pole for above switches	GA016-40C						
GAX41125C	125A		attachable early-make 4th pole for above switches	GA080-125C						
Parallel attachment to convert 3/4 pole switches to 6/8 pole										
<ul style="list-style-type: none"> Used to combine two switches side-by-side to make up a 6/8 pole switch 										
GAX6000			parallel attachment for combining 2 switches (6/8 pole)	GA016-40A						
GAX6001*			parallel attachment for combining 2 switches (6/8 pole)	GA063-125A						
Handles (external front operation) (IP65)										
<ul style="list-style-type: none"> External door interlocking handles padlockable (3 padlocks) in "OFF" position 										
GAX61	red/yellow		door interlocking handle 65mm ² (screw fixing)	GA016-160A/C						
GAX63	red/yellow		door interlocking handle 65 mm ² (ring fix Ø 22 mm)	GA016-160A/C						
GAX64	red/yellow		as above - defeatable 65 mm ² (ring fix Ø 22 mm)	GA016-160A						
GAX68	red/yellow		door interlocking handle 48mm ² (screw fixing)	GA016-40A/C						
GAX66*	red/yellow		door interlocking pistol grip handle - defeatable	GA063-160A						
* Requires GAX60B adaptor (below) and 7mm ² extension shaft										
GAX60B			adaptor to accommodate 7 mm ² shaft required for handles	GAX66/66B						
Extension shafts (for above handles)										
GAX7200	200 mm	5 mm ²	extension shaft for switches	GA016-160A						
GAX7300	300 mm	5 mm ²	extension shaft for switches	GA016-160A						
GAX7200A	200 mm	7 mm ²	extension shaft for switches	GA063-160A						
GAX7300A	300 mm	7 mm ²	extension shaft for switches	GA063-160A						
Auxiliary contact blocks (1th 10A)										
GAX1011A	1NO + 1NC		auxiliary for DIN rail mounting switches	GA016-160A						
GAX1011C	1NO + 1NC		auxiliary for direct door mount switches	GA016-125C						
GAX1110EA	1NO		auxiliary for DIN rail mount switches (early-break)	GA016-40A						
GAX1210EA	1NO		aux for direct door mount switches (early-break)	GA063-160A						
Changeover attachments for switches										
GAX5000			changeover mechanism interlock for 2 switches	GA016-40A						
GAX5001			changeover mechanism interlock for 2 switches	GA063-160A						
GAX67B	black		door interlocking handle (I-O-II) for above changeover mechanisms							