



3631 3003



3841 3003



3831 3015



3821 3063



1443 3111



1401 0540



3999 0600

FUSERBLOC fuse combination switches

FUSERBLOC are manually operated fuse combination switches. They make and break on load and provide safety isolation and protection against overcurrent in any low voltage electrical circuit.

- Complete isolation of fuses with double breaking per pole (*top and bottom of fuse*) with positive break indication
- "Test" position for testing control circuits without power (*up to 400A*)
- External front operating handle and shaft (*to be ordered separately - see below*)
- IEC/EN 60947-3, IEC/EN 60269-1, IEC/EN 60269-2, VDE 0636-1, VDE 0660-107

type	AC-22 A		fuse type	description	dimensions (mm)		
	415V (A)	400V (kW)			(H)	(W)	(D)

NFC cylindrical fuses		3 pole						
3631 3003	CD32A	15kW	10 x 38	fuse combination switch	98	96	65	
3831 3005	50A	25kW	14 x 51	fuse combination switch	118	121	87	
3831 3011	125A	63kW	22 x 58	fuse combination switch	162	148	132	

DIN pattern fuses		3 pole						
3831 3006	63A	30kW	000	fuse combination switch	118	136	132	
3831 3012	125A	63kW	000	fuse combination switch	160	148	132	
3831 3015	160A	80kW	00	fuse combination switch	160	148	132	
3831 3024	250A	132kW	1	fuse combination switch	195	234	146	
3831 3039	400A	220kW	2	fuse combination switch	205	252	149	
3811 3063	630A	355kW	3	fuse combination switch	300	364	250	
3811 3080	800A	450kW	3	fuse combination switch	300	364	250	
3811 3120	1250A	560kW	4	fuse combination switch	300	442	289	

BS88 pattern fuses		3 pole						
3641 3001	CD32A	15kW	A1	fuse combination switch	98	96	83	
3841 3003	32A	15kW	A1	fuse combination switch	118	121	85	
3841 3006	63A	30kW	A2-A3	fuse combination switch	118	136	132	
3841 3010	100A	51kW	A4	fuse combination switch	162	148	132	
3841 3015	160A	80kW	A4	fuse combination switch	162	190	137	
3841 3021	200A	100kW	B1-B2	fuse combination switch	195	234	146	
3841 3024	250A	132kW	B1-B2-B3	fuse combination switch	195	234	146	
3841 3032	315A	160kW	B1-B2-B3	fuse combination switch	205	252	149	
3841 3039	400A	220kW	B2-B3-B4	fuse combination switch	205	252	149	
3821 3063	630A	355kW	C1-C2	fuse combination switch	300	364	250	
3821 3080	800A	450kW	C1-C2-C3	fuse combination switch	300	364	250	
3821 3120	1250A	560kW	D1	fuse combination switch	300	442	289	

Operating handles and accessories for above switches (IP65)

- External front operated, door interlocking, padlockable (*3 padlocks*) in "OFF" with "TEST" position

1413 2115	S1	black	pistol grip operating handle (<i>external</i>)	32 - 63A
1423 2115	S2	black	pistol grip operating handle (<i>external</i>)	100 - 400A
1433 3111	S2	black	pistol grip operating handle (<i>external</i>)	630 - 800A
1443 3111	S4	black	pistol grip operating handle (<i>external</i>)	1250A
1401 0532	S1	320 mm	5 mm	extension shaft for switch CD32A
1401 0540	S1	400 mm	5 mm	extension shaft for switch CD32A
1400 1032	S3	320 mm	10 mm	extension shaft for switch 32 - 400A
1400 1050	S4	500 mm	10 mm	extension shaft for switch 32 - 400A
1400 1232	S3	320 mm	12 mm	extension shaft for switch 630 - 1250A
1400 1250	S3	500 mm	12 mm	extension shaft for switch 630 - 1250A
1429 0000	shaft guide (<i>permits engaging of misaligned shaft with handle</i>)			(<i>all sizes</i>)
3999 0701	1 NO	auxiliary contact block		CD32 - 1250A
3999 0702	1 NC	auxiliary contact block		CD32 - 1250A
3999 0710	contact holder for up to 4 additional auxiliary contacts			CD32A
3999 0600	contact holder for up to 4 additional auxiliary contacts			32 - 400A
3998 3016	3 pole	terminal protection shroud for switches		100 - 160A
3998 3025	3 pole	terminal protection shroud for switches		200 - 400A
3898 3080	3 pole	terminal protection shroud for switches		630 - 800A
3898 3120	3 pole	terminal protection shroud for switches		1250A