



ASR 20.3



ASK 41.4



ASK 51.4



ASK 61.4

Current transformers		Class 1	
General specifications:			
• Nominal frequency:			50Hz (others on request)
• Isolation class:			E
• Nominal thermal short-time current:			$I_{th} = 60 \times I_N$
• Maximum operating voltage:			$U_m \leq 0.72 \text{ kV}$
• Over-current limiting factor:			FS 5 up to 1500 A nominal current

MBS AG current transformers conform fully to: DIN VDE 0414/1 - DIN 42600 - IEC 61869/1+2 - VBG 4

type	ratio	class	Burden (VA)	description	max. hole diameter (mm) round B/bar 1 B/bar 2
Tube/ring type current transformers				5A secondary - class 1	
ASR 20.3 tube current transformers				(H) 65 x (W) 45 x (D) 30 mm	
26027	50/5A	1	1	tube current transformer	
26029	60/5A	1	1.25	tube current transformer	
26031	75/5A	1	1.5	tube current transformer	
26035	100/5A	1	2.5	tube current transformer	
26041	150/5A	1	3.75	tube current transformer	
26051	200/5A	1	3.75	tube current transformer	
26046	250/5A	1	5	tube current transformer	
Busbar mounted current transformers				5A secondary - class 1	
ASK 31.3 current transformers				(H) 76 x (W) 61 x (D) 48 mm	
7038	50/5A	1	1	std current transformer	
7039	60/5A	1	1	std current transformer	
7041	75/5A	1	1.5	std current transformer	
7045	100/5A	1	2.5	std current transformer	
7047	150/5A	1	2.5	std current transformer	
7050	200/5A	1	5	std current transformer	
7053	250/5A	1	5	std current transformer	
ASK 41.4 current transformers				(H) 85.5 x (W) 71 x (D) 58 mm	
13044	100/5A	1	2.5	std current transformer	
13048	150/5A	1	5	std current transformer	
13050	200/5A	1	5	std current transformer	
13054	250/5A	1	10	std current transformer	
13057	300/5A	1	10	std current transformer	
13062	400/5A	1	15	std current transformer	
13066	500/5A	1	15	std current transformer	
13070	600/5A	1	15	std current transformer	
13073	750/5A	1	15	std current transformer	
13077	800/5A	1	15	std current transformer	
ASK 51.4 current transformers				(H) 98.5 x (W) 86 x (D) 58 mm	
16055	400/5A	1	10	std current transformer	
16060	500/5A	1	15	std current transformer	
16064	600/5A	1	15	std current transformer	
16068	750/5A	1	15	std current transformer	
16071	800/5A	1	15	std current transformer	
16075	1000/5A	1	15	std current transformer	
ASK 61.4 current transformers				(H) 105.5 x (W) 96 x (D) 58 mm	
19065	600/5A	1	15	std current transformer	
19069	750/5A	1	15	std current transformer	
19073	800/5A	1	15	std current transformer	
19076	1000/5A	1	15	std current transformer	
19085	1250/5A	1	30	std current transformer	
ASK 81.4 current transformers				(H) 123.5 x (W) 120 x (D) 58 mm	
21045	600/5A	1	10	std current transformer	
21049	750/5A	1	15	std current transformer	
21053	800/5A	1	15	std current transformer	
21056	1000/5A	1	15	std current transformer	
21064	1250/5A	1	15	std current transformer	
21072	1600/5A	1	30	std current transformer	