



ASK 41.4



ASK 61.4



ASK 103.3



ASK 51.4

**Current transformers .../5A Class 0.2 and 0.5**

Modern meters and network analysers provide higher accuracy levels requiring more accurate current transformers. We introduce a range of high accuracy and reliability Class 0.2s and 0.5 Current Transformers.

MBS AG current transformers conform fully to: IEC 60044 / DIN VDE 0414/1 - DIN 42600-2

type	ratio	class	Burden (VA)	description	max. hole diameter (mm)			
					round	B/bar 1	B/bar 2	
<b>Busbar mounted current transformers 5A secondary - Class 0.5</b>								
<b>ASK 41.4</b> current transformers				<i>(H) 85.5 x (W) 71 x (D) 58 mm</i>				
13085	200/5A	0.5	5	std current transformer	<table border="1"> <tr><td>Ø32</td><td>40x10</td><td>30x15</td></tr> </table>	Ø32	40x10	30x15
Ø32	40x10	30x15						
13086	250/5A	0.5	5	std current transformer				
13087	300/5A	0.5	10	std current transformer				
13088	400/5A	0.5	10	std current transformer				
13089	500/5A	0.5	15	std current transformer				
13090	600/5A	0.5	15	std current transformer				
13031	800/5A	0.5	10	std current transformer				
<b>ASK 51.4</b> current transformers				<i>(H) 101.5 x (W) 86 x (D) 58 mm</i>				
16154	600/5A	0.5	15	std current transformer	<table border="1"> <tr><td>Ø44</td><td>50x12</td><td>40x20</td></tr> </table>	Ø44	50x12	40x20
Ø44	50x12	40x20						
16203	750/5A	0.5	15	std current transformer				
16033	800/5A	0.5	15	std current transformer				
16036	1000/5A	0.5	15	std current transformer				
<b>ASK 61.4</b> current transformers				<i>(H) 108.5 x (W) 96 x (D) 58 mm</i>				
19031	800/5A	0.5	15	std current transformer	<table border="1"> <tr><td>Ø44</td><td>63x10</td><td>50x20</td></tr> </table>	Ø44	63x10	50x20
Ø44	63x10	50x20						
19034	1000/5A	0.5	15	std current transformer				
19101	1250/5A	0.5	30	std current transformer				
<b>ASK 81.4</b> current transformers				<i>(H) 126.5 x (W) 120 x (D) 58 mm</i>				
21023	1000/5A	0.5	15	std current transformer	<table border="1"> <tr><td>Ø55</td><td>80x10</td><td>50x30</td></tr> </table>	Ø55	80x10	50x30
Ø55	80x10	50x30						
21029	1250/5A	0.5	15	std current transformer				
21035	1600/5A	0.5	15	std current transformer				
<b>ASK 103.3</b> current transformers				<i>(H) 187.5 x (W) 172 x (D) 52 mm</i>				
23026	1600/5A	0.5	15	std current transformer	<table border="1"> <tr><td>Ø85</td><td>100x30</td><td>80x50</td></tr> </table>	Ø85	100x30	80x50
Ø85	100x30	80x50						
23029	2000/5A	0.5	30	std current transformer				
23032	2500/5A	0.5	30	std current transformer				
23035	3000/5A	0.5	30	std current transformer				
<b>Busbar mounted current transformers 5A secondary - Class 0.2s</b>								
<b>ASK 41.4</b> current transformers				<i>(H) 85.5 x (W) 71 x (D) 58 mm</i>				
V24-1704D	200/5A	0.2s	2.5	std current transformer	<table border="1"> <tr><td>Ø32</td><td>40x10</td><td>30x15</td></tr> </table>	Ø32	40x10	30x15
Ø32	40x10	30x15						
V24-1804F	250/5A	0.2s	5	std current transformer				
V24-1904F	300/5A	0.2s	5	std current transformer				
V24-2004H	400/5A	0.2s	10	std current transformer				
V24-2104H	500/5A	0.2s	10	std current transformer				
V24-2204F	600/5A	0.2s	5	std current transformer				
<b>ASK 51.4</b> current transformers				<i>(H) 98.5 x (W) 86 x (D) 58 mm</i>				
V34-2404H	800/5A	0.2s	10	std current transformer	<table border="1"> <tr><td>Ø44</td><td>50x12</td><td>40x20</td></tr> </table>	Ø44	50x12	40x20
Ø44	50x12	40x20						
V34-2504J	1000/5A	0.2s	15	std current transformer				
<b>ASK 61.4</b> current transformers				<i>(H) 105.5 x (W) 96 x (D) 58 mm</i>				
V41-2704J	1250/5A	0.2s	15	std current transformer	<table border="1"> <tr><td>Ø44</td><td>60x10</td><td>50x20</td></tr> </table>	Ø44	60x10	50x20
Ø44	60x10	50x20						
V41-2804J	1600/5A	0.2s	15	std current transformer				
<b>ASK 123.3</b> current transformers				<i>(H) 184.8 x (W) 172 x (D) 52 mm</i>				
V56-2704F	1250/5A	0.2s	5	std current transformer	<table border="1"> <tr><td>Ø100</td><td>120x30</td><td>100x50</td></tr> </table>	Ø100	120x30	100x50
Ø100	120x30	100x50						
V56-2904J	1600/5A	0.2s	15	std current transformer				
V56-3004J	2000/5A	0.2s	15	std current transformer				
V56-3204J	2500/5A	0.2s	15	std current transformer				
V56-3304J	3000/5A	0.2s	15	std current transformer				