

type	ratio	description	class	VA	dimensions (mm)		
					(H)	(W)	(D)
Class 0.5 current transformers 5A secondary (class 0.2 available on request)							
ASK 41.4 current transformers							
Primary bar conductor:		40 x 10 / 30 x 10mm		Ø round conductor: 32 mm			
13085	200/5A	std current transformer	0.5	5	86	71	40
13086	250/5A	std current transformer	0.5	5	86	71	40
13087	300/5A	std current transformer	0.5	10	86	71	40
13088	400/5A	std current transformer	0.5	10	86	71	40
13089	500/5A	std current transformer	0.5	15	86	71	40
13090	600/5A	std current transformer	0.5	15	86	71	40
ASK 51.4 current transformers							
Primary bar conductor:		50 x 10 / 40 x 20mm		Ø round conductor: 44 mm			
16154	600/5A	std current transformer	0.5	15	99	86	58
16203	750/5A	std current transformer	0.5	15	99	86	58
16033	800/5A	std current transformer	0.5	15	99	86	58
16036	1000/5A	std current transformer	0.5	15	99	86	58
ASK 61.4 current transformers							
Primary bar conductor:		60 x 10 / 50 x 20mm		Ø round conductor: 44 mm			
19031	800/5A	std current transformer	0.5	15	106	96	58
19034	1000/5A	std current transformer	0.5	15	106	96	58
19040	1250/5A	std current transformer	0.5	15	106	96	58
ASK 81.4 current transformers							
Primary bar conductor:		80 x 10 / 60 x 30mm		Ø round conductor: 55 mm			
21023	1000/5A	std current transformer	0.5	15	124	120	58
21029	1250/5A	std current transformer	0.5	15	124	120	58
21035	1600/5A	std current transformer	0.5	15	124	120	58
ASK 103.3 current transformers							
Primary bar conductor:		100 x 30 / 80 x 50mm		Ø round conductor: 85 mm			
23026	1600/5A	std current transformer	0.5	15	188	172	35
23029	2000/5A	std current transformer	0.5	30	188	172	35
23032	2500/5A	std current transformer	0.5	30	188	172	35
23035	3000/5A	std current transformer	0.5	30	188	172	35
Primary wound current transformers 5A secondary - class 1							
WSK 30 primary wound current transformers							
30022	5/5A	wound current transformer	1	5	79	61	35
30024	10/5A	wound current transformer	1	5	79	61	35
30026	15/5A	wound current transformer	1	5	79	61	35
30028	20/5A	wound current transformer	1	5	79	61	35
WSK 40 primary wound current transformers							
31070	25/5A	wound current transformer	1	10	89	71	45
31074	30/5A	wound current transformer	1	10	89	71	45
Summation current transformers 5A secondary - class 1							
KSU 2/3 summation current transformers							
41015	5+5/5A	wound current transformer	1	10	94	127	57
41031	5+5+5/5A	wound current transformer	1	10	94	127	57
SUSK 4 summation current transformers							
40027	5+5+5+5/5A	wound current transformer	1	10	137	156	65



ASK 41.4



ASK 103.3



WSK 40



SUSK 4