



ASK 41.4



ASK 61.4



ASK 103.3

type	ratio	description	class	VA	dimensions (mm)		
					(H)	(W)	(D)
<b>Class 1 1A secondary current transformers</b>							
<b>ASK 41.4 current transformers</b>							
<b>Primary bar conductor:</b>		<i>40 x 10 / 30 x 10 mm</i>		<b>Ø round conductor:</b> 32 mm			
13239	75/1A	std current transformer	1	2.5	86	71	40
13244	100/1A	std current transformer	1	2.5	86	71	40
13248	150/1A	std current transformer	1	5	86	71	40
13250	200/1A	std current transformer	1	5	86	71	40
13254	250/1A	std current transformer	1	10	86	71	40
13257	300/1A	std current transformer	1	10	86	71	40
13262	400/1A	std current transformer	1	15	86	71	40
13266	500/1A	std current transformer	1	15	86	71	40
13270	600/1A	std current transformer	1	15	86	71	40
55012	DIN rail adaptor for above current transformers						
<b>ASK 51.4 current transformers</b>							
<b>Primary bar conductor:</b>		<i>50 x 10 / 40 x 20 mm</i>		<b>Ø round conductor:</b> 44 mm			
16260	500/5A	std current transformer	1	15	99	86	58
16264	600/5A	std current transformer	1	15	99	86	58
16268	750/5A	std current transformer	1	15	99	86	58
16271	800/5A	std current transformer	1	15	99	86	58
16275	1000/5A	std current transformer	1	15	99	86	58
<b>ASK 61.4 current transformers</b>							
<b>Primary bar conductor:</b>		<i>60 x 10 / 50 x 20 mm</i>		<b>Ø round conductor:</b> 44 mm			
19265	600/5A	std current transformer	1	15	106	96	58
19269	750/5A	std current transformer	1	15	106	96	58
19273	800/5A	std current transformer	1	15	106	96	58
19277	1000/5A	std current transformer	1	30	106	96	58
19285	1250/5A	std current transformer	1	30	106	96	58
<b>ASK 81.4 current transformers</b>			<i>current transformers</i>				
<b>Primary bar conductor:</b>		<i>80 x 10 / 60 x 30mm</i>		<b>Ø round conductor:</b> 55 mm			
21253	800/1A	std current transformer	1	15	124	120	40
21256	1000/1A	std current transformer	1	15	124	120	40
21264	1250/1A	std current transformer	1	15	124	120	40
21272	1600/1A	std current transformer	1	30	124	120	40
<b>ASK 103.3 plug-in current transformers</b>			<i>current transformers</i>				
<b>Primary bar conductor:</b>		<i>100 x 30 / 80 x 50 mm</i>		<b>Ø round conductor:</b> 85 mm			
23251	1250/1A	std current transformer	1	30	188	172	35
23258	1600/1A	std current transformer	1	30	188	172	35
23262	2000/1A	std current transformer	1	30	188	172	35
23266	2500/1A	std current transformer	1	30	188	172	35
23270	3000/1A	std current transformer	1	30	188	172	35